

[FARmudding@gmail.com](mailto:FARmudding@gmail.com) wants to thank you for purchasing a Halo Kit!

Do **NOT** cut **OR** shorten the wires of halos, When cleaning halos avoid direct contact with high-pressure water sources that may harm the coating and void the warranty. All halos are bench-tested before shipment. A switch is provided for you to splice into the positive and ground (red(+) and black(-) Leads) and use the switch to power on and off the halos. **When wiring or testing halos. Always power off, when making connections.** Scan the QR code on the box to install the app. **Or** plug in the remote piece depending on which set you ordered.

### How to install the Chasing Halo Kit:

We always recommend that you remove the headlights from the vehicle. You will need to clean the area with rubbing alcohol and make sure the headlight is free of dirt and debris. Peel the double-sided tape and stick it on each halo, run wires as necessary.

Now that you have secured the halo light to the machine's headlight housing and allowed it to set up, you can start connecting it to a 12v power supply.

To properly supply 12v to each halo you may choose several options:

1. You may splice directly to your headlights (power supply) so they turn On and OFF with the headlights
2. You can choose to splice into the accessory plug (12v accessory plug) allowing the lights to turn on and off with the key separate from the headlights
3. You may use the positive wire to the battery and the negative wire to the battery or a ground close by and then with a switch to turn them On and OFF with Our switch provided (gold negative)  
(2 silver Positive)



Post your pics and tag us [@FARMUDDING](https://www.instagram.com/FARMUDDING)

Follow Us on FACEBOOK: [facebook.com/FARmudding](https://www.facebook.com/FARmudding)